Quick Reference Manual 5618 CASIO

Congratulations upon your selection of this CASIO watch.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by CASIO COMPUTER CO., LTD. is under license

This product has a Mobile Link function that lets it communicate with a Bluetooth® capable phone to perform automatic time adjustment and other operations.

• This product complies with or has received approval under radio laws in various

- countries and geographic areas. Use of this product in an area where it does not conform to or where it has not been approved under applicable radio laws may be punishable under local laws. For details, visit https://world.casio.com/ce/BLE/. Use of this product inside of an aircraft is restricted by the aviation laws of each
- country. Be sure to obey instructions provided by flight personnel concerning use of devices such as this product.


Visit the website below for the operation manual (Operation Guide) of this watch.

https://world.casio.com/manual/wat/



Using the Watch

General Guide




- 1. Auto Light enabled
- 2. Hands shifted
- 3. Summer time display indicator
- 4. p.m. indicator (No indication for a.m.)
- 5. Phone connected*
- 6. World Time Mode indicator
- 7. Alarm Mode indicato
- 8. Airplane Mode enabled
- 9. Alarm enabled
- 10. Hourly time signal enabled
- 11. Mode hand operation is linked with operations
- * Hold down (1) for about two seconds to establish a Bluetooth connection with a phone.

Selecting a Mode

Each press of (C) cycles between modes as shown below.

Hold down © for at least two seconds to enter the Timekeeping Mode



Setting the Time

- In the Timekeeping Mode, hold down
 B. Release the button when the city name appears.
- . [SET] will flash and then the city name



2. Press © three times display the seconds setting screen.



- 3. Press (1) to reset the seconds count to 00.
- 30 to 59 seconds: Adds 1 to minutes.
- Press © to move the flashing to the hour setting.
- 5. Use (A) and (D) to change the setting. 6. Press © to move the flashing to the
- minute setting.
 Use (A) and (D) to change the setting.
- Press © twice to move the flashing to the year setting. 9. Use (A) and (D) to change the setting.
- 10. Press © to move the flashing to the
- month setting. 11. Use (A) and (D) to change the setting.
- Press © to move the flashing to the day setting.
- 13. Use (A) and (D) to change the setting.
- 14. Press (B) to exit the setting screen.

Specifications

Accuracy at Normal ±15 seconds per month average when time adjustment by

communication with a phone is not possible Analog Timekeeping: Hour, minute (moves every 20 seconds)

Digital Timekeeping:

Hour, minute, second, month, day, day of the week, a.m./p.m. (P)/24-hour timekeeping, Full Auto Calendar (2000 to 2099), Summer Time

Measurement unit: 1/1000 seconds (first hour); Stopwatch:

1/10 seconds (after first hour)
Measurement range: 23 hours, 59 minutes, 59.9 seconds
Measurement functions: Normal elapsed time; lap times

Measuring unit: 1 second Countdown range: 24 hours

Setting unit: 1 second

10-second beeper at countdown end

Current time in 38 cities (38 time zones) plus UTC time; summer time; Home City/World Time swapping World Time:

5 Daily alarms; Hourly time signal Setting units: Hour, minute Alarm tone duration: 10 seconds

Hourly time signal: Beep every hour on the hour

Mobile Link: Auto time correction

Phone finder

Phone finder
Watch operation sounds the alert sound of the mobile phone.
World Time
Current time for approximately 300 cities selected for the watch
Home Time/World Time swapping
Stopwatch data transfer

200 lap time records (date and time, lap time, lap number)

Auto summer time switching

Automatic switching between standard time and summer time

Hand position correction

Schedule timer Schedule Irrier
Links with your phone's calendar, and uses the watch's hands
and digital display to show a countdown of the time until
completion of an event, ending time, etc.

Data Communication Specifications
Bluetooth®

Engagement Appl. (200 MHz to 2400 MHz)

Frequency band: 2400 MHz to 2480 MHz

Maximum transmission: 0 dBm (1 mW)
Communication range: 2 meters max. (depends on environment)

Double LED Illumination: Face LED and digital display LED with Auto Light, Super Illuminator, afterglow, selectable illumination duration (1.5 seconds, 3 seconds); button operation tone on/off; schedule notification tone on/off; date display (month/day, day/month); day of the week display (6 languages); Airplane Mode; Hand Shift; low battery alert

One lithium battery (CR2016) Power Supply:

Approximate Battery Life:

Other:

Alarms

Bluetooth connection time: 12 hours/day
 Alarm: Once (10 seconds)/day
 Illumination: Once (1.5 seconds)/day

Specifications are subject to change without notice